# Low Pass Filter

#### DC<sup>(1)</sup> to 2500 MHz $50\Omega$

## LFCN-2500+



Generic photo used for illustration purposes only CASE STYLE: FV1206

+RoHS Compliant

The +Suffix identifies RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications



## Reel Size Devices/Reel 20, 50, 100, 200, 500,1000, 3000

## **Maximum Ratings**


Operating Temperature	-55°C to 100°C
Storage Temperature	-55°C to 100°C
RF Power Input*	10W max at 25°C


<sup>\*</sup> Passband rating, derate linearly to 3.5W at 100°C ambient. Permanent damage may occur if any of these limits are exceeded

#### Pin Connections

RF IN	1_
RF OUT	3
GROUND	2,4

## Outline Drawing





Suggested Layout, Tolerance to be within ±.002

#### **Features**

- · excellent power handling, 10W
- small size
- 7 sections
- temperature stable
- LTCC construction
- protected by U.S Patent 6,943,646

### **Applications**

- harmonic rejection
- VHF/UHF transmitters/receivers
- lab use


## Electrical Specifications(1,2) at 25°C

Pa	Parameter		Frequency (MHz)	Min.	Тур.	Max.	Unit
Pass Band	Insertion Loss	DC-F1	DC-2500	_	_	1.0	dB
	Freq. Cut-Off	F2	3075	_	3.0	_	dB
	VSWR	DC-F1	DC-2500		1.2	_	:1
Stop Band	Rejection Loss	F3	3675	20	_	_	dB
		F4-F5	3800-6100	_	30	_	dB
		F6	8000	_	20	_	dB
	VSWR	F3-F6	3675-8000	_	20	_	:1

(1) In Applications where DC isolation to ground is required, coupling capacitors are recommended to avoid DC leakage. Alternatively, if DC pass IN-OUT is required, Mini-Circuits' "D" suffix version of this model will support DC IN-OUT, and provide>100 MOhm isolation to ground. (2) Measured on Mini-Circuits Characterization Test Board TB-270.

# Typical Frequency Response F1 F2 F3 F4 FREQUENCY






## Outline Dimensions (inch )

	G	F	E	D	C	В	Α
	.169	.009	.032	.020	.037	.063	.126
	4.29	0.23		0.51		1.60	3.20
	1.20	0.20	0.01	0.01	0.0 1	1.00	0.20
wt	Р	N	M	L	K	J	Н
grams	.071	.012	.087	.024	.122	.024	.087
.020	1.80	0.30	2.21	0.61	3.10	0.61	2.21

## Demo Board MCL P/N: TB-270 Suggested PCB Layout (PL-137)



COPLANAR WAYEGUIDE PARAMETERS ARE SHOWN FOR ROGERS ROA\$50B WITH THICKNESS .020" ± .0015". COPPER: 1/2 02. EACH SIDE. FOR OTHER MATERIALS TRACE WIDTH & GAP MAY NEED TO BE MODIFIED.

DENOTES DESCRIPTION OF THE PCB IS CONTINUOUS GROUND PLANE.


DENOTES PCB COPPER LAYOUT WITH SMOBC (SOLDER MASK OVER BARE COPPER)

DENOTES COPPER LAND PATTERN FREE OF SOLDER MASK

### Typical Performance Data at 25°C

Frequency (MHz)	Insertion Loss (dB)	VSWR (:1)	
50.00	0.05	1.02	
2000.00	0.50	1.26	
2530.00	0.80	1.24	
3000.00	2.72	2.58	
3660.00	24.30	23.81	
3760.00	29.63	28.03	
4000.00	43.19	31.03	
5000.00	34.98	26.33	
6000.00	34.38	24.48	
7000.00	26.29	26.74	
8000.00	22.85	27.59	
10000.00	19.22	18.30	
12000.00	14.60	13.09	
15000.00	17.48	3.73	
20000.00	15.48	4.84	





Notes
A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.
B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.
C. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp